


Product data sheet

eNet radio centre plate



Reference number

FMA1701XX

eNet radio centre plate

for LB Management inserts "blinds" ref.-no.: 1730 JE and 1731 JE
 for LB Management inserts "light" ref.-no.: 1701 SE, 1704 ESE, 1702 SE, 1710 DE,
 1711 DE, 1713 DSTE, 1723 NE

Intended use

- Manual, radio-controlled and time-controlled operation of e.g. blinds, shutters, awnings, lighting or fans
- Transmitter for radio communication of switching, dimming and blind commands
- Operation with switch, dimmer or blinds insert or satellite insert 3-wire of the LB Management

Product characteristics

- 2 switching times can be saved, which are repeated in a 24-hour cycle
- Disabling function
- Status feedback to radio transmitter
- Status indication with LED
- Night mode
- Evaluation of satellite inputs

Functions in combination with blinds insert

- Positioning of the blind/shutter via scene request
- Position for sun protection and twilight
- Running time and ventilation position of the blind/shutter can be saved

Functions in combination with light insert

- Scene operation possible
- Switch-on brightness can be saved permanently when combined with flush-mounted inserts for dimming

Functions in combination with relay switch insert 2-channel

- Output a2 switches depending on output a1 e.g. to switch on ventilation, depending on the lighting, and switch it off with a delay.
- Switch-on delay of output a2 adjustable
- Run-on time of output a2 adjustable

Can be set with eNet server from version 2.2 (depending on insert):

- Repeater function
- Slat change-over time/fabric-stretching time
- Change-over time for direction change
- Running direction invertible
- Operating locks
- Deactivating extension evaluation
- Position for sun protection, twilight, lock-out protection and wind alarm
- Maximum brightness

- Minimum brightness
- Dimming speed
- Switch-on delay / switch-off delay
- Dim up/dim down ramp
- Switch-off warning
- Continuous on, Continuous off
- Hotel function
- Run-on time
- Light control

Supplementary functions with eNet server:

- Fully-encrypted radio transmission (AES-CCM)
- Update of the device software
- Reading of error memory

