




KNX RF Multi USB interface

Product	Order number	VE	PP
 KNX RF Multi USB interface	3-0003-006	1	1

Technical data

Rated voltage:	DC 5 V
KNX medium:	KNX RF Ready (from ETS5) KNX RF Multi (from ETS6)
Current consumption:	25 mA
Frequency (KNX RF Ready):	868.3 MHz
Frequency (KNX RF Multi):	868.3 MHz, 868.950 MHz, 869.525 MHz, 869.850 MHz
Transmission power:	max. 25 mW
Transmission range in free field:	100 m (typical)
USB connection:	2.0 type A
Ambient temperature:	-10°C to +55°C
Dimensions:	approx. 21 mm x 59 mm x 7.5 mm

Information

Convenient and wireless access to a KNX installation from a PC or laptop. The device serves as an interface to KNX installations via radio using the KNX RF standards RF Ready and RF Multi.

Features:

- Support of KNX RF Multi
- Support of KNX RF Ready
- Wireless communication between PC and KNX RF
- Commissioning and troubleshooting via ETS6 (KNX RF Multi) or ETS5 (only KNX RF Ready)
- Support of long frames
- Enables commissioning of RF Secure devices
- No additional USB driver required

The product may slightly differ from the illustration.