## 4,3" KNX Capacitive Touch Panel with IP Connectivity and Door Phone Function




240612-0

### **MAIN FEATURES**

4,3" capacitive touch panel for visualisation and control of KNX installations, featuring a IPS display, IP connectivity for remote control from smartphones and tablets, and door phone function. Available in white or black GLASS finish, can be installed in portrait or landscape mode.

- Function highlights:
  - Up to 96 control functions, organized in 12 configurable pages
  - User editable favorites page
  - Configurable background images
  - Weekly time schedules (up to 96 channels, 4 programs / channel)
  - Alarm monitoring (up to 96 alarms) with event log
  - Touch gestures: up to 5 quick actions (4 directions + multitouch), even with the display off (power saving mode)
  - o Internal scene controller
  - o Two independent thermostats
  - o Video door phone function (\*), with full duplex audio and echo cancellation
  - IP camera monitoring (\*)
- Remote control from smartphones and tablets via mobile apps
- Four multi-function inputs, individually configurable as binary or temperature probe inputs
- Real-time clock (RTC) with backup battery
- Integrated KNX bus coupling unit
- Ultra-low power consumption

(\*) Please check compatibility



### **TECHNICAL SPECIFICATIONS**

	Form factor		Wall mounted unit	
Mechanical	Enclosure material		ABS FR V0	
	Degree of protection		IP20	
	Weight		160 g / 210 g (excluding / including mounting chassis)	
	Magnetic fixing		4x gold-plated N50 neodymium magnets (pull: 4x 1.2 kg)	
	Mounting box		Standard square or rounded flush mounting box (not included) Iddero part numbers: E-C466 / E-C456	
Environment	Storage temperature		-2070 °C	
	Operating temperature		055 °C	
	Relative humidity		1090% (non-condensing)	
	Supply voltage		12-30 VDC	
External power supply			Do not use 29 VDC from KNX bus as external power supply	
	Power consumption		Max. 5 W	
			Typ. 165 mA (12 VDC), 85 mA (24 VDC), 75 mA (30 VDC)	
	Connection		Pluggable terminal block, 3.5 mm pitch	
	Recommended wiring		Conductor section 0.5 mm <sup>2</sup>	
	Power supply unit		Not included	
	Display	Туре	Widescreen 4,3" TFT display, IPS technology	
User interface		Resolution	272 x 480 pixels	
		Colour	24 bpp (16.7 million colours)	
		Contrast ratio	800:1 (Typ.)	
		Backlight	Low power white LED backlight, with energy saving mode	
		Luminance	Typ. 450 cd/m <sup>2</sup> , software controlled	
		Viewing angle	Typ. 80° (all directions)	
		Touch screen	Projected capacitive multitouch	
		Cover glass	0.7mm tempered high visibility glass, chemically strengthened	
	Audio	Speakers	1W + 1W stereo loudspeakers	
		Microphone	Integrated microphone	

www.iddero.com






		Buttons	KNX programming button (recessed)	
User interface	Other	Indicators	KNX programming LED Buzzer	
Communications	KNX	Туре	KNX TP1 bus	
		Connection	Standard KNX TP1 connector	
		Consumption	Typ. 4 mA @ 29 VDC	
	Ethernet	Туре	Ethernet 10/100 BASE-T interface	
		Connection	Pluggable terminal block, 2.5 mm pitch	
		Rec. wiring	Twisted pair, 0.2 mm <sup>2</sup> section (CAT5), solid wires	
Expansion port		Туре	USB 2.0	
	USB	Connection	Micro-USB type B connector	
		Output power	150 mA max.	
	Number of inputs		4 independent inputs	
	Туре		Individually configurable as binary (push button and switch/sensor	
	Туре		modes) or temperature probe inputs	
	Connection		Pluggable terminal block, 3.5 mm pitch	
	Rec. wiring		Conductor section 0.2 to 1.5 mm <sup>2</sup>	
Inputs	Binary inputs	Contact type	Dry voltage contact between the two input terminals	
		Detection time	Typical 50 ms (switch/sensor mode)	
		Pulse width	Minimum 10 ms (push button mode)	
		Cable length	Maximum recommended length: 50 m	
	Temp. probe		External temperature probe, ref. TS-N1PB / TS-GLASS	
Real time clock	Drift		+/-20 ppm @ 25°C	
Real tille Clock	Battery backup		CR1220 3V, 35 mAh	
Compliance	Directives		Directive 2014/30/EC	
			Directive 2011/65/EC	
			Directive 2012/19/EC	
	Standards		EN 50491-5-1:2010	
			EN 50491-5-2:2010	
			EN 50581:2012	
			EN 50419:2006	

Specifications subject to change without notice







### **CONNECTORS AND OTHER ELEMENTS**



- 1. Power supply connector (12-30 VDC)
- 2. KNX programming button
- 3. KNX programming LED
- 4. KNX TP1 bus connector
- 5. Microphone
- 6. USB connector
- 7. Multifunction inputs connector
- 8. Loudspeakers
- 9. Replaceable RTC backup battery
- 10. Ethernet connector

### Input connection





Temperature probe refs.: Iddero TS-N1PB / TS-GLASS

### **Ethernet wiring**

VERSO INDOOR	Description	RJ45
1	TX-	2
2	TX+	1
3	RX-	6
4	RX+	3











### **RTC** battery replacement





### **DIMENSIONS**

















IMPORTANT: Only qualified electricians should install, service, or manipulate this equipment. Existing regulations for the prevention of accidents must be observed, as well as any national or local codes and regulations and standard safety precautions.



This product is an electronic device containing batteries, and must not be disposed of in household waste. At the end of its life cycle, the product must be taken to an electric and electronic waste collection facility. Before that, batteries must be removed from the device and taken to a battery collection point.



## INSTALLATION NOTES: 1. Select installation height to allow for direct line of sight 2. Do not expose to direct sun light

N N


- DE


# INSTALLATIONSANMERKUNGEN: 1. Wählen Sie eine Installationshöhe, die eine direkte Blicklinie ermöglicht 2. Installieren Sie dieses Produkt nicht im direkten Sonnenlicht

- NOTAS DE INSTALACIÓN: 1. Seleccionar la altura de instalación de forma que permita línea de visión directa 2. No instalar en lugares donde la luz solar incida directamente ES
- NOTES D'INSTALLATION:

  1. Selectionnez la hauteur d'installation de façon qu'elle permette ligne de visée directe

  2. Ne pas exposer directement au soleil FR











7

\_











က

\_

≥ 40






CLICK!





230425-03











4

